



# TYPE RXLSK AC REVERSING STARTERS 3 PHASE FULL VOLTAGE



All Starters Supplied with BUILT-IN HEATERS

Size 00-2



NEMA RATED

AC-1 AMPS	AC-3 AMPS	Horse Power (UL) Ratings 3 Phase Motor Max UL HP	OPEN	ENCLOSED					Comparable NEMA HP NEMA Size	
				NEMA 1 General Purpose	NEMA 4X Outdoor (non-metal)	NEMA 4 (metal)	NEMA 3R (metal)	NEMA 12 Dust Tight (metal)		
20A	9A	200V 3 HP 230V 3 HP 460V 5 HP 600V 5 HP	<b>See Page 77</b>							
25A	9A	200V 3 HP 230V 3 HP 460V 5 HP 600V 7.5 HP LIST	RXLS4K -★0-★★ \$238	RXLS4K -★1-★★ \$328	RXLS4K -★4x-★★ \$394	RXLS4K -★4-★★ \$437	RXLS4K -★3R-★★ \$375	RXLS4K -★12-★★ \$427		
25A	12A	200V 3 HP 230V 3 HP 460V 7.5 HP 600V 10 HP LIST	RXLS5K -★0-★★ \$262	RXLS5K -★1-★★ \$352	RXLS5K -★4x-★★ \$418	RXLS5K -★4-★★ \$451	RXLS5K -★3R-★★ \$398	RXLS5K -★12-★★ \$441	200V 1.5 HP 230V 1.5 HP 460V 2 HP 600V 2 HP <b>NEMA 00</b>	
32A	18A	200V 5 HP 230V 5 HP 460V 10 HP 600V 15 HP LIST	RXLS7K -★0-★★ \$273	RXLS7K -★1-★★ \$363	RXLS7K -★4x-★★ \$429	RXLS7K -★4-★★ \$465	RXLS7K -★3R-★★ \$412	RXLS7K -★12-★★ \$455		
45A	25A	200V 5 HP 230V 7.5 HP 460V 15 HP 600V 15 HP LIST	RXLS11K -★0-★★ \$308	RXLS11K -★1-★★ \$398	RXLS11K -★4x-★★ \$464	RXLS11K -★4-★★ \$499	RXLS11K -★3R-★★ \$424	RXLS11K -★12-★★ \$489	200V 3 HP 230V 3 HP 460V 5 HP 600V 5 HP <b>NEMA 0</b>	
60A	32A	200V 10 HP 230V 10 HP 460V 20 HP 600V 25 HP LIST	RXLS15K -★0-★★ \$418	RXLS15K -★1-★★ \$508	RXLS15K -★4x-★★ \$574	RXLS15K -★4-★★ \$608	RXLS15K -★3R-★★ \$568	RXLS15K -★12-★★ \$598		
60A	40A	200V 10 HP 230V 10 HP 460V 25 HP 600V 25 HP LIST	RXLS18K -★0-★★ \$463	RXLS18K -★1-★★ \$553	RXLS18K -★4x-★★ \$619	RXLS18K -★4-★★ \$750	RXLS18K -★3R-★★ \$705	RXLS18K -★12-★★ \$740	200V 7.5 HP 230V 7.5 HP 460V 10 HP 600V 10 HP <b>NEMA 1</b>	
90A	50A	200V 15 HP 230V 15 HP 460V 30 HP 600V 40 HP LIST	RXLS22K -★0-★★ \$524	RXLS22K -★1-★★ \$734	RXLS22K -★4x-★★ \$799	RXLS22K -★4-★★ \$985	RXLS22K -★3R-★★ \$784	RXLS22K -★12-★★ \$975		
110A	65A	200V 20 HP 230V 20 HP 460V 40 HP 600V 50 HP LIST	RXLS30K -★0-★★ \$674	RXLS30K -★1-★★ \$884	RXLS30K -★4x-★★ \$949	RXLS30K -★4-★★ \$1,170	RXLS30K -★3R-★★ \$897	RXLS30K -★12-★★ \$1,160		
110A	80A	200V 20 HP 230V 25 HP 460V 50 HP 600V 60 HP LIST	RXLS37K -★0-★★ \$768	RXLS37K -★1-★★ \$978	RXLS37K -★4x-★★ \$1,259	RXLS37K -★4-★★ \$1,255	RXLS37K -★3R-★★ \$982	RXLS37K -★12-★★ \$1,245	200V 10 HP 230V 15 HP 460V 25 HP 600V 25 HP <b>NEMA 2</b>	

**Steps To Order Motor Starter:**

**Step 1-Size** Choose from the UL HP and Voltage list per your application.  
For example: 5 HP 230V 3 phase part # RXLS7K.

**Step 2 - Coil\*** From the coil suffix chart on the next page choose the suffix for your control circuit voltage requirement. (Example: 24VAC = G-) (Part # RXLS7K-G)

**Step 3 -Enclosure** specify "open" or "enclosed" requirements.  
For example if NEMA 12 (part #RXLS7K-G12-).

**Step 4 -Overload Amps\*\*** This step requires a suffix for your overload protection, refer to "OVERLOAD RELAY SUFFIX TABLE" (next page)  
(Example: 5HP @ 230V 3 Phase, if 13 Full Load Amps = suffix "N".)  
Example: RXLS7K- G12 - N

**RXLSK Series Starters**

- (what's included?)
- AEG 3 Phase Reversing Starters.
- (Ambient compensated Bi metallic windings).
- -25°C - +60°C (-11.20°F - +140°F).
- Overload Class 10 (adjustable heaters).
- Electrical & Mechanical interlocks as standard.
- Thru door reset. Enclosed units only).

Modifications and accessories are listed on pages 65, 68

For Operators, Transformers & Accessories see page 60