

SERIES D

25 - 250 AMP

600 VOLT

PADLOCKABLE

ON - OFF

SINGLE HOLE MOUNT

FRONT DRILLING
22mm, 7/8"

OPTION
30.5mm
Full size PB mount



3 POLE	SIZE UNIT	RATED CURRENT		WITH BE OPERATOR		WITH D OPERATOR	
		I _{TH} AMPS	UL/CSA GENERAL PURPOSE (INDUCTIVE) AMPS	CATALOG NUMBER	LIST PRICE	CATALOG NUMBER	LIST PRICE
	D1	25	25	E D1-3BE 1 SH-*	\$60	E D1-3D 2 SH-*	\$69
	D2	40	40	E D2-3BE 2 SH-*	88	E D2-3D 2 SH-*	97
	D3	63	63	E D3-3BE 2 SH-*	121	E D3-3D 2 SH-*	130
	DK4	80	80	-	-	-	-
	D4	100	100	-	-	-	-
	D5	125	125	-	-	-	-

4 POLE	D1	25	25	E D1-4BE 1 SH-*	\$70	E D1-4D 2 SH-*	\$79
	D2	40	40	E D2-4BE 2 SH-*	102	E D2-4D 2 SH-*	111
	D3	63	63	E D3-4BE 2 SH-*	134	E D3-4D 2 SH*	144
	DK4	80	80	-	-	ADAPTOR RING To convert standard 22mm switch (7/8" mounting) to full size 30.5mm #ED-134353 \$0.80 list each	
	D4	100	100	-	-		
	D5	125	125	-	-		

2 Pole (Size D1 Only)

Deduct \$10 from List Price

P/N Example: Change 3 to 2: E D1-3BE (3 Pole)

E D1-2BE (2 Pole)

* SUFFIX: Add -RG for Red-Yellow operator handle.

Add -SS for Black handle "D" type only.

Add -SI for Black-Silver operator "BE" handle.

DISCONNECT DESCRIPTION PLATE FITS ABOVE TYPE BE OR D OPERATORS

MAIN SWITCH	DESCRIPTION	CATALOG NUMBER	LIST PRICE			
			48 X 16mm (1.9" X 0.6")		65 X 6mm (2.5" X 0.8")	
MAIN SWITCH	BRUSH SILVER WITH BLACK LETTERS	ED-NP-	-S1	\$10	-S2	\$11
	YELLOW WITH BLACK LETTERS	ED-NP-	-Y1	\$10	-Y2	\$11
MAIN SWITCH	BLACK WITH WHITE LETTERS	ED-NP-	-B1	\$10	-B2	\$11

Standard marking add suffix: Main Switch (-MS) OR Emergency off (-EO).

For special marking add \$6 List.

Example: #ED-NP-S1

Dimensions: See page 205.